

eFlow104NBV — Power Supply/Charger

Description

Altronix eFlow104NBV power supply/charger converts a 220VAC (working range 198VAC - 256VAC), 50/60Hz input into a single 24VDC output. It also offers a suite of features that includes fire alarm disconnect, overvoltage protection, and low power disconnect which prevents deep discharge of stand-by batteries.

Altronix®

eFlow104NBV

Input		Indicators (LED)		
Voltage	220VAC, 50/60Hz, 2.7A max.	Input	220VAC is present.	
•	6.3A / 250V.	•	Powered.	
Fusing	0.3A7230V.	DC Output	Powereu.	
Outputs		Agency Listings		
Voltage	24VDC.	CE	European Conformity.	
Current	10A continuous max.			
Auxiliary	1A (unswitched).	Physical and Environmental		
Other	Overvoltage protection.	Dimensions (L x W x H)		
	Filtered and regulated.	8.25" x 4.56" x 1.5"	8.25" x 4.56" x 1.5" (209.5 mm x 115.8 mm x 38.1 mm).	
		Product Weight	1.1 lbs. (0.5 kg).	
Back-up Battery (not included)		Shipping Weight	1.25 lbs. (0.57 kg).	
Туре	Sealed lead acid or gel type.	Temperature		
Fuse Rating	15A @ 32VDC.	Operating	0°C to 49°C (32°F to 120°F).	
Failover	Upon AC loss, instantaneous.	Storage	-20°C to 70°C (-4°F to 158°F).	
		Relative Humidity	85% +/-5%.	
Fire Alarm Disconnect		BTU/Hr (approx.):	123 BTU/Hr.	
Supervised	Latching or non-latching.	Mounting hardware included.		
EOL	10K Resistor.			
Supervision				
AC Failure	Form "C" contacts.			
Battery	Form "C" contacts.			
71-73% for 12V u	Shutdown tput terminals if battery voltage drops below nits and 70-75% for 24V units power supply). Prevents deep battery discharge			

Accessories

Network Supervision

Altronix model LINQ2 Network Communication Module provides remote supervision, control and monitoring over LAN/WAN

- Remotely reports accurate power diagnostics
- Controls power and resets devices
- Reports system diagnostics via Email









Board Dimensions (L x W x H) and Drawing

8.25" x 4.56" x 1.5" (209.5 mm x 115.8 mm x 38.1 mm)

