

## eFlow4NV Series Power Supply/Chargers

### Description

Altronix eFlow4NV series power supply/chargers convert a 220VAC (working range 198VAC - 256VAC), 50/60Hz input into a single fused or eight (8) fuse/PTC protected outputs. Power supply/charger is selectable for 12VDC or 24VDC with a total of 4A max. They also offer a suite of features that includes fire alarm disconnect, overvoltage protection, and low power disconnect which prevents deep discharge of stand-by batteries.



eFlow4N8V

### Key Features

- Available with 1 or 8 outputs.
- Fused or PTC protected outputs.
- Additional Aux. Output rated @ 1A.
- Overvoltage protection.
- Fire alarm disconnect.
- Supervision
  - AC Fail
  - Battery Fail and Battery Presence
  - Low power shutdown.
- Built-in charger for sealed lead acid or gel type batteries.
- Instantaneous transfer to stand-by batteries.
- Short circuit and overload protection.
- AC input and DC output LED indicators.
- CE Approved.
- Lifetime Warranty / Made in the U.S.A.

### eFlow4NV series Power Supply Configuration Reference Chart

Altronix Model Number	Nominal DC Outputs				Maximum Supply Current for Main and Aux. Outputs (A)	Input Rating: 220VAC, 50/60Hz	Input Fuse Rating	Battery Fuse Rating	Ripple Voltage (mV) Under low battery condition	Power Distribution Module	Number of Outputs	Fused Outputs Ratings	Auto-Resettable PTC Outputs Ratings	Accommodates up to 7AH Batteries	Accommodates up to 12AH Batteries
	[DC]		[AUX]												
	12VDC Output Range (volts)	24VDC Output Range (volts)	12VDC Output Range (volts)	24VDC Output Range (volts)											
eFlow4NV	10.1-13.2	20.28-26.4	10.05-13.2	20.2-26.4	4A	2.1A	5A/250V	7.5A/32V	730	N/A	1	-	-	✓	-
eFlow4NXV												-	-	-	✓
eFlow4N8V	10.1-13.2	20.28-26.4	10.05-13.2	20.2-26.4	4A	2.1A	5A/250V	7.5A/32V	730	PD8	8	2.5A	-	✓	-
eFlow4NX8V												2.5A	-	-	✓
eFlow4N8DV	9.78-13.2	20.28-26.4	10.05-13.2	20.2-26.4	4A	2.1A	5A/250V	7.5A/32V	730	PD8CB	8	-	2A	✓	-
eFlow4NX8DV												-	2A	-	✓



## eFlow4NV Series Power Supply/Chargers



### Specifications

#### Input

Voltage	220VAC (working range 198VAC - 256VAC), 50/60Hz, 2.1A max.
Fuse Rating	5A/250V.

#### Outputs

Voltage	12VDC or 24VDC selectable.
Current	4A continuous max.
Protection	Fused 2.5A / PTC 2A.
Auxiliary	1A (unswitched).
Other	Overvoltage protection Filtered and regulated.

#### Back-up Battery *(not included)*

Capacity	7AH / 12VDC (1 or 2 within enclosure). 12AH / 12VDC (requires larger "X" enclosure). 40AH, 65AH (requires separate enclosure).
Type	Sealed lead acid or gel type.
Fuse Rating	7.5A/32VDC.
Failover	Upon AC loss, instantaneous.

#### Fire Alarm Disconnect

Supervised	Latching or non-latching.
EOL	10K Resistor.

#### Supervision

AC Failure	Form "C" contacts.
Battery	Form "C" contacts.

#### Low DC Power Shutdown

Shuts down DC output terminals if battery voltage drops below 71-73% for 12V units and 70-75% for 24V units (depending on the power supply). Prevents deep battery discharge.

#### Indicators (LED)

Input	220VAC is present.
DC Output	Powered.

#### Agency Listings

CE	European Conformity
----	---------------------

#### Physical and Environmental

##### Dimensions (H x W x D)

eFlow4NV, eFlow4N8(D)V:  
13.5" x 13" x 3.25" (342.9mm x 330.2mm x 82.55mm).  
eFlow4NXV, eFlow4NX8(D)V:  
15.5" x 12" x 4.5" (393.7mm x 304.8mm x 114.3mm).

##### Product Weight / Shipping (approx.)

Model	Product Weight	Shipping Weight
eFlow4NV	6.55 lbs. (2.97 kg)	7.45 lbs (3.38 kg)
eFlow4NXV	8.4 lbs. (3.81 kg)	9.5 lbs (4.3 kg)
eFlow4N8(D)V	6.7 lbs. (3.04 kg)	7.6 lbs (3.45 kg)
eFlow4NX8(D)V	8.55 lbs. (3.88 kg)	9.65 lbs (4.38 kg)

#### Temperature

Operating	0°C to 49°C (32°F to 120°F).
Storage	-20°C to 70°C (-4°F to 158°F).

Relative Humidity 85% +/-5%.

#### BTU/Hr (approx.):

12VDC: 25 BTU/Hr.  
24VDC: 49 BTU/Hr.

### Accessories

#### Network Supervision

Altronix model **LINQ2** Network Communication Module provides remote supervision, control and monitoring over LAN/WAN

- Remotely reports accurate power diagnostics
- Controls power and resets devices
- Reports system diagnostics via Email

