

# PYRAMID

## KEYBOARD

PY-KBD...

<b>PY-KBD-L</b>	RS485, Low speed
<b>PY-KBD-2-H</b>	RS485, High speed
<b>PY-KBD-H</b>	FTT10, High speed



### FEATURES

- Compact, ergonomic design
- Full functional control of all camera functions when used with Pyramid receiver
- Control of all RS232 devices (Multiplexers, VCRs, etc.)
- Joystick with integrated pan, tilt and zoom

### Specifications

**Display** 24 x 2 character LCD. Displays camera number, monitor number and softkey assignments

**Controls** Multiplexer  
VCR  
Monitor select  
Camera select  
Receiver preset select  
Receiver auxilliary control  
Lens focus and iris adjustment  
Receiver sequencer, random and patrol  
Programmable Softkeys  
Function keys  
Numerical keys  
3 axis joystick controlling pan, tilt and zoom

**RS232 Control** VCR - Play, record, fast forward, rewind, frame advance, frame reverse, stop and time modes  
Multiplexer - Encode/decode, freeze, zoom, multi-picture/full picture select and time modes

**SmartCard Access** 255 access levels and resources. Read/write PIN (4 digit). Multiple privelege levels.

**Material** ABS end caps with aluminium and mild steel case

**Dimensions** 450 x 140 x 60mm

**Power supply** Remote network access box (PY-NAP) with plug-in mains PSU

**Power consumption** 6W nominal

**Weight** 2kg

**Connections** RJ45



**BAXALL LIMITED**