

8 Zone Control Panel

Securit 800L

8 Zone Control Panel

Versatile Installation
User-Friendly Design
Easy to Operate Remote Keypad



SPECIFICATIONS

Eight Zones Alarm:	6 Programmable for: Alarm, Entry/Exit, Access (walk through), Personal Attack, Part Set Entry, Part Set Isolation. 1 Programmable for: Entry, Alarm, Fire, Keyswitch. 1 Fixed: Entry/Exit.
Home Set Facility:	Gives flexibility by automatically isolating pre-programmed zones, allowing the system to b armed while the User remains inside.
Manual Isolation:	The system can be tailored for any situation that arises by isolating individual zones which have not been programmed for Home or Part Set Isolation.
Remote P.A. option:	The Remote keypads can be programmed to give a Personal Attack Feature, using the * and $^{\#}$ Keys.
Extension Speaker Output:	For greater enhanced sounds, up to two 16 Ohm extension speakers can be fitted.
Chime Function:	Enabling this feature allows Monitoring of chosen zones while the panel is disarmed.
Two User Codes:	Main User code plus second code for children or cleaner etc.
Securit 800L CONTROL PANEL	
Dimensions:	261mm x 266mm x 88mm (h x w x d)
Material:	White, epoxy powder coated, 18 swg shell
Weight:	3.10 Kg
Mains Supply Voltage:	230 V AC Nominal
PSU Output Voltage:	13.6 V Nominal
Maximum Output Current:	1 A (total)
Event Memory:	Allows checking of past events
Panel Quiescent:	40 mA.
Normal Operating Temperature:	0°C to 40°C
Humidity:	10 to 90% R.H. non-condensing
KEYPAD	
Dimensions:	70mm x 120mm x 25mm (h x w x d)
Weight:	0.13 Kg
Supply Voltage:	12V
Quiescent Current:	20 mA.
Active:	45 mA.
Maximum Number Allowed:	Six
Approvals:	CE Designed to comply with BS4737 Part I
Order Part Number:	ST800L-UI

Honeywell Security
Honeywell International Inc.
2 Redwood Crescent
East Kilbride
G74 5PA
Scotland
Tel +44 (0)1355 354000
www.honeywell.com/security/uk/intruder

