AV COSTAR[®]

ConteraCMR[®] NVR Appliance

20TB Max Storage 24 Max Channel Count Cloud Managed Recorder with Dual NIC or Single NIC and Built-in 8 and 16 Port PoF Switch



AV Costar[™] ConteraCMR[®] NVR Appliance is designed to offer powerful IP recording in an affordable, compact chassis. The NVR Appliance is available in two configurations - A dual NIC standard NVR or a single NIC with an on-board 8 or 16 channel PoE switch. With a capacity of 24 channels, the NVR Appliance supports Plug and Play connection with AV Costar and ONVIF cameras, or RTSP video streams. With full integration to ConteraWS Web Services,

the NVR Appliance offers centralized user management, single sign-on convenience, mobile apps and a web client that allows for easy remote connection to your recorders. Network setup is fast and easy using ConteraWS Web Services, and eliminates the need for port forwarding or DDNS. The ConteraCMR NVR Appliance runs on a secure Linux® OS and comes preloaded with ConteraVMS® Server software as a turn key solution.













Dual Gigabit NICs

Cloud Management

Cloud Video ConteraVMS® Export and Sharing



Up to 20TB

SSD OS Drive

een





Linux Standard OS



Integrated PoE Switch

Series Features

- Cloud Management with ConteraWS
- ConteraVMS Ready
- · Cloud Video Export and Sharing
- 2, 4, 6, 8, 12, 16, or 20TB Storage Capacity
- 2 Hard Disk Drives (HDDs)
- Linux OS
- Built-in PoE Switch
- Dual NIC or Single NIC with 8 and 16 Port Built-in PoE Switch
- 24 Max Channel Count
- IP Channel Upgrades
- Solid State OS Drive (SSD)
- Intel[®] Celeron[®] Processor
- 3-Year Hardware Warranty
- 1-Year Advanced Replacement

1 24 channels can be achieved on PoE switch models by using multi-sensor cameras, or by connecting a switch to one of the PoE ports.



Centralized User Management

ConteraWS provides secure storage of all user profile information, allowing role-based management for hundreds of users and device permissions.



Health Monitoring

Cloud-based health monitoring ensures your cameras and recorders are working properly and minimum recording retention levels are being met.



Alerts and Reports

ConteraWS grants insight into operational events at recorder locations and provides valuable business intelligence based on customer or employee activity.



Single Sign-on

Log into ConteraWS Web Services, ConteraVMS, and Arecont Vision Mobile using the same email address and password.



Clip Sharing

Export video clips to the cloud so they cannot be overwritten or lost. Share video clips via email with password protection.



ConteraCMR° NVR Appliance

Specifications

Recorder Specifications

| Model | | AV-CV | AV-CVP08 | AV-CVP16 | | |
|-------------|-----------------------------|---|---|----------|--|--|
| Recording | Max IP Channels | 24 | | | | |
| | Max IPS Per Channel | 30IPS (dependent on camera settings) | | | | |
| | Built-in PoE Ports | None | 8 | 16 | | |
| | Recording Resolutions | | Up to 12MP (dependent on camera settings) |) | | |
| | Recording Rate | 100Mbps | | | | |
| | Maximum Display Resolution | 4К | | | | |
| | Image Compression | H.264 | | | | |
| Connections | Video Outputs | 2 x HDMI (Multi-monitor display is not supported) | | | | |
| | USB Ports | | Front: 1 x USB 3.0 Rear: 2 x USB 3.0 | | | |
| Software | Video Signal Loss Detection | Yes | | | | |
| | Motion Detection | AV Costar camera side or ONVIF Profile S server side | | | | |
| | Remote Operation | ConteraVMS thick client / thin (web) client / mobile apps | | | | |
| | User Management | Web or local based user permissions and account management | | | | |
| | Recording Mode | Continuous / Motion / Continuous + Motion | | | | |
| | Playback Search | Multi-channel playback (1, 4, 9) / Calendar / Timeline / Thumbnail / Event (VMS and web client) | | | | |
| | Clip Backup | Cloud / Network / USB | | | | |
| | Digital Signature Support | AVI and JPG | | | | |
| | Web Connect | Yes | | | | |
| | Operating System | Linux | | | | |

General

| Network | Dual NIC | Dual gigabit NICs | |
|--|--------------------------------------|--|--|
| Network | PoE | Single gigabit NIC + 8 or 16 Port PoE Switch | |
| Keyboard and Mouse | Included | | |
| DVD Drive | N/A | | |
| PoE Switch Load | 8CH | 120W | |
| | 16CH | 200W | |
| Operating Temperature | 32°F ~ 104°F (0°C ~ 40°C) | | |
| OS Drive Configuration | eMMC SSD | | |
| Storage Configuration | Dual NIC | Up to 20TB | |
| | 8CH PoE | Up to 16TB | |
| | 16CH PoE | Up to 20TB | |
| Mounting Hardware | Rack mount installation kit included | | |
| Warranty | 3 Years, 1 yea | ar advanced replacement | |
| System Control | Keyboard, mouse (included) | | |
| Compliance | | | |
| IP Camera Support AV Costar / ONVIF Profile S / RTSP | | NVIF Profile S / RTSP | |
| Certification | UL certified, CE, FCC | | |
| CoO Made in Taiwan | | an | |

Electrical

| Power | Dual NIC | 40W max |
|--------------|----------|--|
| Consumption | 8CH PoE | 160W max |
| | 16CH PoE | 240W max |
| Power Supply | Dual NIC | 60W external (Input: 100-240V, 2.0A, 50/60Hz) |
| | 8CH PoE | 200W internal (Input: 100~240VAC, 3.5A, 50-60Hz) |
| | 16CH PoE | 280W internal (Input: 100~240VAC, 6.3A, 50-60Hz) |

Mechanical

| Dimensions (See Dimensions) | Unit | 14.4" W (366mm) x 1.8" H (46mm) x 12.6" L (316mm) | | |
|--------------------------------|----------|--|-----------------|--|
| | Packaged | 22" W (558.8mm) x 8" H (203.2mm) x 22" L (558.8mm) | | |
| Weight | Dual NIC | Unit | 8.2lbs (1.59kg) | |
| | | Packaged | 18lbs (8.16kg) | |
| | 8CH PoE | Unit | 8.6lbs (1.59kg) | |
| | | Packaged | 18lbs (8.16kg) | |
| | 16CH PoE | Unit | 9lbs (2.27kg) | |
| | | Packaged | 18lbs (8.16kg) | |


ConteraCMR® NVR Appliance

Specifications


Controls and Connections




Rear Panel - Dual NIC



Rear Panel - Single NIC + PoE Switch



Dimensions



ConteraCMR® NVR Appliance

Ordering Information

Rev 003.001





Single NIC with Built-in 8 or 16 Port PoE Switch

Dual NIC


Model Numbers

| Dual NIC | AV-CV-04T |
|-----------|--------------|
| | AV-CV-06T |
| | AV-CV-08T |
| | AV-CV-12T |
| | AV-CV-16T |
| | AV-CV-20T |
| PoE 8 CH | AV-CVP08-2T |
| | AV-CVP08-4T |
| | AV-CVP08-6T |
| | AV-CVP08-8T |
| | AV-CVP08-12T |
| | AV-CVP08-16T |
| PoE 16 CH | AV-CVP16-4T |
| | AV-CVP16-6T |
| | AV-CVP16-8T |
| | AV-CVP16-12T |
| | AV-CVP16-16T |
| | AV-CVP16-20T |
| | |

Software and Service Licenses

| Part Number | Description | |
|--|---|--|
| ConteraVMS | | |
| ConteraVMS Software Licenses | | |
| AV-CST1 | ConteraVMS Standard 1 Channel Recording License | |
| AV-CPM1 | ConteraVMS Premium 1 Channel Recording License | |
| AV-CPR1 | ConteraVMS Professional 1 Channel Recording License | |
| ConteraVMS Software Expansion Licenses | | |
| AV-CST1-EXP | ConteraVMS Standard 1 Channel Expansion Recording License | |
| AV-CPM1-EXP | ConteraVMS Premium 1 Channel Expansion Recording License | |
| AV-CPR1-EXP | ConteraVMS Professional 1 Channel Expansion Recording License | |
| ConteraVMS Software Upgrade Licenses | | |
| AV-CSUBAPM | ConteraVMS Standard to Premium 1 Channel License Upgrade | |
| AV-CSUPMPR | ConteraVMS Premium to Professional 1 Channel License Upgrade | |
| ConteraWS | | |
| ConteraWS (Web Services) Access License Including Software Updates | | |
| AV-CWS1Y | ConteraWS 1 Year 1 Channel Access License | |
| AV-CWS3Y | ConteraWS 3 Year 1 Channel Access License | |
| AV-CWS4Y | ConteraWS 4 Year 1 Channel Access License | |
| AV-CWS5Y | ConteraWS 5 Year 1 Channel Access License | |
| ConteraWS (Web Services) Cloud Storage Expansion | | |
| AV-CWS1Y50GB | ConteraWS 50GB Cloud Storage Expansion (1 Year) | |

Create Your Model (Example: AV-CVP16-20T)



+1.818.937.0700 | www.avcostar.com | avsales@arecontvision.com

© 2021 Arecont Vision Costar, LLC. All rights reserved. Arecont Vision, Contera, ConteraCMR, ConteraVMS, and ConteraWS are registered trademarks of the company. AV Costar and the AV Costar logo are business use trademarks of the company.