

2MP Box Camera

TC-B1202

- Full HD (1080p) resolution
- C / CS Mount Lens
- Day&Night (ICR)
- WDR (Wide Dynamic Range: 15fps)
- Motion Detection
- De-fog
- HSBLC
- OSD Control over Coax



SPECIFICATIONS

| VIDEO | |
|-----------------------------|---|
| Image Sensor | 1/2.8" SONY 2Mega Exmor CMOS Sensor |
| Effective pixels | 1984(H) X 1105(V), 2.19M Pixels |
| Total pixels | 2000(H) X 1121(V), 2.24M Pixels |
| Max. Resolution | 1920 X 1080 |
| Scanning Mode | Progressive Scan |
| Lens Type | C/CS Mount Lens |
| IRIS Control | DC Auto Iris / Manual Iris |
| Min. illumination | COLOR : 0.9 Lux @ F1.8 B/W : 0.6 Lux @ F1.8 |
| S/N Ratio | More than 50dB |
| Electronics Shutter Speed | AUTO / Manual(1/30,1/25Sec ~ 1/30000Sec) / FLICKER |
| Day/Night | YES(ICR) |
| Video Out | 1 HD BNC , 1 SD BNC |
| FUNCTION | |
| AGC | 0 ~ 20 Level Adjustable |
| Brightness | 0 ~ 20 Level Adjustable |
| Sens-UP | OFF / x2 ~ x32 |
| WDR(Wide Dynamic Range) | OFF / ON (Low,Middle,High / 15 Frame) |
| Backlight Compensation(BLC) | OFF/ON |
| HSBLC | 1 ~ 20 Level Adjustable(ALL DAY/NIGHT ONLY) |
| ACE(D-WDR/ATR-EX) | OFF/LOW/MIDDLE/HIGH |
| Motion Detection | OFF/ON (4 Zone) |
| Privacy Masking | OFF/ON (16 Zone) |
| Day & Night | Auto(AGC)/Color/B&W/EXTERN |
| Smart-IR(IR OPTIMIZER) | - |
| White Balance | AUTO(2,500K ~ 9,500K) / AWB(1,800K ~ 10,500K) / AWC--Set / Manual |
| Digital Noise Reduction | 2D+3DNR(OFF/LOW/MIDDLE/HIGH) |
| Mirror | MIRROR,V-FLIP |
| D-ZOOM(EZOOM) | X1 ~ X8 |
| Sharpness | 0~20 Level Adjustable |
| De-fog | OFF/ON |
| GAMMA Correction | r = 0.45 ~ 0.65 |
| Lens Shading(LSC) | OFF/ON |
| ENVIRONMENTAL | |
| Out-door Ready | - |
| Storage Temperature | -20°C~ +60°C(-4°F~ +140°F) (Humidity : 0% ~ 95%) |
| Operating Temperature | -10°C~ +50°C(14°F~ +122°F) (Humidity : 0% ~ 90%) |
| ELECTRICAL | |
| Power Source | 12VDC, 24VAC |
| Power Consumption | 2.64W |
| MECHANICAL | |
| Dimensions (W x H x D) | 58mm x 52mm x 123mm (2.29" x 2.05" x 4.85") |

DIMENSIONS

(Unit - mm)



ACCESSORIES(OPTIONAL)



DA-BH1100

DA-WM1500

ACCESSORIES CONFIGURATION TREE

