CONTROL PANELS

AVANTI **AVANTI RADIO**

8 Zone Hardwired Panel

8 Zone Hybrid Wireless Panel

Applications:

A flexible and fully featured security control panel providing a cost effective solution to both domestic and light industrial applications. Avanti Radio is compatible with the Keystone 006 Series of transmitters.

General Specifications for both Panels:

No of Codes: No of Keypads: 4 max **Event Log:** 16

Bell/Siren Output: 12V (0V switched)

Bell/Siren Timer: 0-99 mins programmable **Entry/Exit Timers:** 0-99 secs programmable Extension Speaker: Maximum of 2 x 6 ohms

Strobe Output: 12V latch till reset or bell follow **Current Cons:** CPU st/by 70mA Alarm 200mA RKP st/by 40mA Alarm 70mA

Construction: Polycarbonate. 0 to 40 degrees C **Operating Temp:** Standards: EN50131-1-6

LVD 72/23/EEC EMC Directive 89/336EEC

R&TTE Directive (Wireless)

Hybrid Wireless Panel Specifications:

No of Zones: 4 Self Learn Wireless + 3 Wired Remote Arm/Disarm (5th RF zone **Keyfob:**

available if not required)

Transmitter Low Battery and Tamper Indication





Features:

8 Zones + PA + Tamper

All zones fully programmable as one of 5 types: Immediate, Timed, Time Inhibited, Fire or Doorbell

Programs

3 different part set programs

Active in Day or Set modes

Tamper

Full alarm in Set mode, local in Day mode

Communicator Outputs (RS panels only) Intruder, PA ,Fire, Set, Confirmed, Abort

All zones can be programmed for Chime

Zone Bypass

All zones can be temporarily bypassed

Walk Test Mode

Simple wireless and wired sensor placement

test

Tape Dialler Output

Product No Description Model

Avanti	K600 K600RS	8 Zone Hardwired Panel with built-in Keypad As K600, but with 6 communicator outputs
Avanti Radio	K600RF	Hybrid Panel with 4 Wireless Zones + 3 Hardwired Zones + Remote Arm/Disarm Built-in Keypad
	K600RF RS	As K600RF, but with 6 communicator outputs
Avanti RKP	K600RKP	Additional Hardwired LED Keypads

