

### **WV-CP280**

### **Static Cameras**

High performance digital signal processor

Superb image quality and cost performance

Adaptive Black Stretch technology

Day/Night operation can be selected automatically or manually

Back Light Compensation (BLC) mode selector



Cost-effective Colour Surveillance Camera with Adaptive Black Stretch Technology

#### null

General	
Туре	Colour Surveillance Camera
Pick-up Device	1/3-type interline transfer CCD
Effective Pixels	
Horizontal	752.0
Vertical	582.0
Scanning Area [mm]	
Horizontal	4.9
Vertical	3.7
Signal	PAL
Synchronization	Internal (INT), Multiplexed Vertical Drive (VD2), Line-Lock (LL), selectable
Scanning Mode	2:1 interlace
Scanning Frequency	
Horizontal [KHz]	15.625
Vertical [Hz]	50.0
Resolution	
Horizontal	540 TV lines (Colour)

## **Panasonic**

### ideas for life

Vertical	-
Dynamic Range	-
Signal-to-Noise Ratio	50 dB minimum (AGC: OFF)
Minimum Illumination (Colour)	0.8 lux
Minimum Illumination (B/W)	-
Weather Protection	-
Power Source	
Voltage AC [V]	220-240
Voltage DC [V]	0.0
Frequency [Hz]	50.0
Power Consumption [W]	3.2
Ambient Operating Temperature [degrees C]	
Minimum	-10.0
Maximum	50.0
Ambient Operating Humidity [%]	
Minimum	0.0
Maximum	90.0
Dimensions [mm]	
Width	67.0
Height	65.0
Depth	139.5
Weight [kg]	0.51
Finish	
Main Functions	
Controller Interface	Coaxial
Auto Gain Control (AGC)	Always On
Zoom Speed	-
Focus Speed	-
Iris / Light Control	ALC/ELC
Shutter	-
Motion Detector	-
Auto Focus	-
Back Light Compensation (BLC	) ON/OFF
Sensitivity Enhancement	-
White Balance	ATW
Camera Title	16 alphanumeric characters
Privacy Zone	-

# Panasonic ideas for life

Image Stabilizer	-
Adaptive Black Stretch	ON/OFF
Detail / Aperture Level	-
Colour/Mono Switching	ON/OFF
Mirror	-
Language Setting	English, German, French, Italian, Spanish, Russian, Chinese, Japanese
Lens	
Туре	CS-mount CS-mount
Zoom Ratio	-
Iris Range / Aperture Ratio	-
Angular Field of View	
Horizontal	-
Vertical	-
Maximum Aperture Ratio	-
Input/Output	
Video Output	VBS: 1.0V [p-p] PAL composite 75 Ohms (BNC plug)
Alarm Output	-