## **COV-SMO**

## **Covert Camera In A Domestic Smoke Detector.**

Monochrome models offering good response to Infra-red illumination.

Suitable for covert viewing onto staircases.

All models fitted with an internal microphone as standard for Audio monitoring.



Sensor Interline CCD **Exposure Control** Electronic 12V DC Voltage

**AGC** Always on

Video Signal Composite into  $75\Omega$ 

-10 °C to +50 °C Operating Temp.

Relative Humidity 85% Max. non-condensing On-board Audio Line-level output

Mass 150 grammes

## Connections

The camera is fitted with a four way lead for connection to video and power cables.


**RED** - 12V DC power

**BLUE** - 0V / Signal Ground (& Co-axial screen) Video signal YELLOW (Co-axial core) **GREY** - Audio signal

Suitable screened cable should be used to achieve optimum video performance. The camera requires as regulated 12V DC power supply.

The Video and Audio signals use the 0V connection as Ground.

ORDER CODE
COV-SMO-C
ens fitted is a 3.7 mm



The smoke detection mechanism operates from a single 9V PP3 battery, (not included)

Please note: The positioning of the COV-SMO may be determined by the required view of the camera.

If this is not the optimum location for smoke detection then this unit should not be relied on as a smoke alarm.

©2003 Stortech Electronics Ltd PECAN is the CCTV division of Stortech Electronics Ltd.

Telephone 01279 419913

www.Stortech.co.uk